




Datasheet

HCA-400M-5K-C

High Speed Current Amplifier



Features	<ul style="list-style-type: none"> • Bandwidth DC ... 400 MHz • Rise / Fall Time 1 ns • Optimized for Low Pulse Distortion – Almost No Overshoot or Ringing will Occur • Transimpedance (Gain) 5×10^3 V/A 	
Applications	<ul style="list-style-type: none"> • Photodiode and Photomultiplier Amplifier • Spectroscopy • Ionisation Detectors • Ideal for Analyzing Digital Signals (No Baseline Shift at any Digital Code) • Preamplifier for A/D Converters, Digitizers etc. 	
Specifications	<i>Test Conditions</i>	<i>Vs = ± 15 V, Ta = 25°C</i>
Gain	Transimpedance	5×10^3 V/A (@ 50 Ω load)
	Gain Accuracy	± 2 %
Frequency Response	Lower Cut-Off Frequency	DC
	Upper Cut-Off Frequency (- 3 dB)	400 MHz (± 10 %, @ Csource 2 to 4 pF)
		350 MHz (± 10 %, @ Csource 5 to 10 pF)
	Max. Source Capacitance	10 pF (incl. cable, e.g. typical coax cable 1 pF/cm)
	Rise / Fall Time (10 % - 90 %)	1.0 ns (@ Csource 2 to 4 pF)
		1.3 ns (@ Csource 5 to 10 pF)
	Gain Flatness	± 0.3 dB
Input	Equ. Input Noise Current	21 pA/√Hz (@ 100 MHz)
	Equ. Input Noise Voltage	3.5 nV/√Hz (@ 100 MHz)
	Equ. Integrated Noise	4 μA peak-peak (independent of Csource)
	Input Bias Current	2 μA typ.
	Input Bias Current Drift	0.07 μA / °C
	Offset Current Compensation	± 200 μA, adjustable by offset trimpot
	Input Current Range	± 200 μA (for linear amplification)
	Input Offset Voltage	< 2 mV
	DC Input Impedance	50 Ω (virtual) // 5 pF
Output	Output Voltage Range	± 1.0 V (@ 50 Ω load) for linear operation and low harmonic distortion
	Max. Output Voltage Range	± 1.5 V (@ 50 Ω load)
	Output Impedance	50 Ω (terminate with 50 Ω load for best performance)
Bias Output	Bias Output Voltage Range	± 12 V, adjustable by bias trimpot
	Bias Output Impedance	10 kΩ // 1 μF

Datasheet



HCA-400M-5K-C

High Speed Current Amplifier

Specifications (continued)		
Power Supply	Supply Voltage	$\pm 15\text{ V}$
	Supply Current	$\pm 60\text{ mA typ.}$ (depends on operating conditions, recommended power supply capability minimum $\pm 150\text{ mA}$)
Case	Weight	210 g (0.5 lbs)
	Material	AlMg4.5Mn, nickel-plated
Temperature Range	Storage Temperature	$-40 \dots +100\text{ }^\circ\text{C}$
	Operating Temperature	$0 \dots +60\text{ }^\circ\text{C}$

Absolute Maximum Ratings	Input Voltage	$\pm 5\text{ V}$
	Power Supply Voltage	$\pm 22\text{ V}$

Connectors	Input	BNC
	Output	BNC
	Power Supply	LEMO series 1S, 3-pin fixed socket
		Pin 1: $+15\text{ V}$
		Pin 2: -15 V
		Pin 3: GND




High Speed Current Amplifier

Typical Performance Characteristics

Frequency Response


Offs 16.0 dB RBW 3 MHz
 Att 0 dB * VBW 10 kHz M1[1] -2.94 dB
 Ref -4.0 dBm SWT 130ms 410.000000000 MHz



Start 20.0 MHz Stop 800.0 MHz

Noise Spectrum

Att 0 dB RBW 3 MHz
 Ref 22.4 mV * VBW 3 kHz Noise2 219.730591 nV/√Hz
 SWT 180ms Noise1 102.946035 nV/√Hz



Start 0.0 Hz Stop 800.0 MHz


Note: Spectral noise data is measured at the amplifier output with open but shielded input. To determine the spectral input noise divide the measured output noise by the amplifier gain of 5×10^3 V/A, i.e.:

Marker	Frequency	Output Noise	Resulting Input Noise
1	100 MHz	103 nV/√Hz	21 pA/√Hz
2	580 MHz	220 nV/√Hz	44 pA/√Hz


High Speed Current Amplifier

Typical Performance Characteristics (continued)

Pulse Response to Square Wave Input Signal (with 16 times averaging)





Large Signal Response
output signal for 100 MHz, 200 μ A peak-peak input signal (with 4 times averaging)



High Speed Current Amplifier

Typical Performance Characteristics (continued)

Small Signal Response
output signal for 1 MHz, 2.4 μ A peak-peak square wave input signal (without (top) and with 64 times averaging (bottom))




Datasheet

HCA-400M-5K-C

High Speed Current Amplifier

Dimensions



DZ01-0201-22

FEMTO Messtechnik GmbH
 Klosterstr. 64
 D-10179 Berlin · Germany
 Tel.: +49-(0)30-280 4711-0
 Fax: +49-(0)30-280 4711-11
 e-mail: info@femto.de
<http://www.femto.de>

Specifications are subject to change without notice. Information furnished herein is believed to be accurate and reliable. However, no responsibility is assumed by FEMTO Messtechnik GmbH for its use, nor for any infringement of patents or other rights granted by implication or otherwise under any patent rights of FEMTO Messtechnik GmbH. Product names mentioned may also be trademarks used here for identification purposes only.

© by FEMTO Messtechnik GmbH
 Printed in Germany