

FEATURES

- Single-chip CMOS construction
- Driver 4 digit multiplexed LCD with PM/AL-time, Alarm Chime mark.
- Colon display.
- Direct drive of piezoelectric transducer
- 32,768 Hz crystal frequency.
- Single 1.5V battery operation.
- On chip oscillator, capacitor, resistor and voltage doubler

FUNCTIONS

- 5 Functions: month, date, hour, minutes, & second.
- 30- second alarm sound.
- 4- year calendar.
- Chime on every hour
- User Selective 12-hour / 24- hour format.
- One-touch correction of time error within ± 30 seconds.
- 2-switch sequential operating.
- LCD test.
- Alarm chime enable / disable

DESCRIPTION

SS0849 is a CMOS 5-function watch integrated circuit with alarm function that provides to drive a 4- digit multiplexed liquid crystal display with colon, PM / AL-time and AL/CH mark.

ABSOLUTE MAXIMUM RATING ($T_a = 25^\circ\text{C}$)


Characteristic	Symbol	Value	Unit
Supply Voltage	$V_{DD} - V_{SS}$	-0.3 + 2.0	V
Operation Temperature	T_a	-20 + 75	$^\circ\text{C}$
Storage Temperature	T_{stg}	-40 + 125	$^\circ\text{C}$

ELECTRICAL CHARACTERISTICS ($T_a = 25^\circ\text{C}$, $V_{SS} = -1.5\text{V}$, $V_{DD} = 0\text{V}$, UNLESS OTHERWISE SPECIFIED)

Characteristic	Symbol	Test Conditions	Min	Type	Max	Unit
Operating Voltage	V_{SS}		-1.8	-1.5	-1.2	V
Operating Voltage	V_{EE}		-3.6	-3.0	-2.4	V
Supply Current	I_{DD}	Without Load		1.0	2.0	μA
Input Low Voltage	V_{IL}		V_{SS}		$V_{SS} + 0.3$	V
Input High Voltage	V_{IH}		$V_{DD} - 0.3$		V_{DD}	V
Switch Activation Current	I_{SW}	$V_{IN} = V_{DD}$	0.1	10	3.0	μA
Oscillator Start Voltage	V_{OSC}	Within 5 Sec	-1.45			V
Oscillator Stop Voltage	V_{OSP}		-1.15			V
Alarm drive current	I_{ALA}	$V_{sat} = 0.5\text{V(BothDir)}$	0.5	2.0		mA
Oscillator Frequency	F_{OSC}			32,786		Hz
DC-DC Conversion Frequency	F_{CON}	$C1 = C2 = 0.1\mu\text{F}$		1024		Hz
LCD Frequency	F_D			32		Hz
Oscillator input capacitor	C_{IN}			20		pF
Time Stability	T_{stb}	$V_{SS} = -1.3 \sim -1.8\text{V}$		1	3	ppm
SW Debouncing Time	T_{ded}				62.5	msec


APPLICATION CIRCUIT

SS0849






ALARM OUTPUT WAVEFORM

4096 Hz (50%Duty)




4096Hz (50%Duty)





PAD DIAGRAM

SS0849



Pad No	Name	Pad No	Name
1	VDD	17	G4/A4
2	I/O	18	E4/F4
3	CAP	19	C3/B3
4	S	20	G3/AD3
5	T1	21	E3/F3
6	T2	22	D4/COLON
7	T3	23	C2/B2
8	VEE	24	G2/A2
9	VDD	25	E2/F2
10	VSS	26	D2/B1
11	D	27	C1/ADEF1
12	AL2	28	PM/AL
13	AL1	29	COM2
14	COM1	30	OSCI
15	CHIME/ALARM	31	OSCO
16	C4/B4		

欢迎索取免费详细资料、设计选型指南和光盘、样品；产品繁多未能尽录，欢迎来电查询。

[中国传感器科技信息网：HTTP：//WWW.SENSOR-IC.COM/](http://WWW.SENSOR-IC.COM/)

[工控安防网：HTTP：//WWW.PC-PS.NET/](http://WWW.PC-PS.NET/)

[消费电子专用电路网：HTTP://WWW.SUNSTARE.COM/](http://WWW.SUNSTARE.COM/)

E-MAIL：xjr5@163.com szss20@163.com

MSN：suns8888@hotmail.com

QQ：195847376

地址：深圳市福田区福华路福庆街鸿图大厦 1602 室

电话：0755-83376549 83376489 83387030 83387016

传真：0755-83376182 83338339 邮编：518033 手机：(0)13902971329

深圳展销部：深圳华强北路赛格电子市场 2583 号 TEL/FAX：
0755-83665529 25059422

北京分公司：北京海淀区知春路 132 号中发电子大厦 3097 号

TEL：010-81159046 82615020 13501189838 FAX：010-82613476

上海分公司：上海市北京东路 668 号上海赛格电子市场 2B35 号

TEL：021-28311762 56703037 13701955389 FAX：021-56703037

西安分公司：西安高新开发区 20 所(中国电子科技集团导航技术研究所)
西安劳动南路 88 号电子商城二楼 D23 号

TEL：029-81022619 13072977981 FAX:029-88789382

成都：TEL:(0)13717066236

技术支持：0755-83394033 13501568376