


Magnetometers

PC BOARD LEVEL 3-AXIS FLUXGATE MAGNETOMETER

- ▼ Complete 3-axis System
- ▼ Measures Fields up to ± 1 Gauss ($\pm 100 \mu\text{T}$)
- ▼ Low Noise Level
 $<1 \times 10^{-6}$ Gauss rms/Hz $^{1/2}$
- ▼ Low Cost PC Board Configuration

Applications

- ▼ OEM Magnetic Field Measuring
- ▼ Fluxgate Compass System
- ▼ Magnetic Anomaly Detection




CXM113

The CXM113 is a complete 3-axis fluxgate magnetometer system packaged on a PC board of dimensions 2.5" x 2.5" x 0.75" (6.4cm x 6.4cm x 1.9cm). The system operates from an input voltage of ± 5 VDC. Current consumption is 28 mA @ +5 V and 7 mA @ -5 V. The system is connected by 6" long flying leads.

The CXM113 provides 3 analog output voltages proportional to the magnetic field magnitude measured in three orthogonal directions. The full-scale output is ± 4.0 volts; representing a magnetic field of ± 1.00 Gauss. Output scale factor is adjusted to an accuracy of 1%. The system noise level is $<1 \times 10^{-6}$ Gauss rms/Hz $^{1/2}$. As a magnetic compass, the CXM113 can provide direction accuracy better than 0.1° .

For magnetic anomaly detection applications, the low noise level of the CXM113 allows very small magnetic signatures to be measured. This enables signal detection at a large distance from the anomaly being measured. Range to the anomaly can be measured by using several CXM113s to record both field magnitude and field gradient. Range is proportional to the quotient of these quantities.

A calibration sheet is provided with each unit giving data on zeros, scale factors, and orthogonality constants for each axis. This data enables an external correction of the output voltages to increase overall accuracy.




Specifications	CXM113
Performance	
Range (Gauss)	± 1
Noise Level (Gauss rms/Hz ^{1/2})	$< 1 \times 10^{-6}$
Frequency Response (Hz)	DC to 400 (-3 dB)
Non-Linearity (% FS)	± 0.1
Zero Drift with Temperature (mGauss/°C)	< 0.1
Scale Factor Drift with Temperature (% FS/°C)	< 0.1
Sensitivity (V/Gauss)	4.00
Othogonality of Axes (°)	± 0.2
Alignment of Axes w/ Package Reference Frame (°)	± 0.2
Environment	
Operating Temperature (° C)	- 20 to + 70
Electrical	
Power	+ 5V @ 28 mA and -5 V @ 7 mA
Physical	
Size	2.5" x 2.5" x .75" (6.4 cm x 6.4 cm x 1.9 cm)
Weight	0.975 oz (30 gm)
Leads	Flying leads 6" (15.24 cm) long


Wire Color	Function
Red	+5 VDC
Black	Ground
Blue	-5 VDC
Orange	X-axis output
Yellow	Y-axis output
Green	Z-axis output

Pin Diagram


Specifications subject to change without notice



Analog Output 3-Axis Magnetometer Board



The CXM113 is Calibrated Using a Precision 3-axis Helmholtz Coil



magnetometers

Ordering Information

Model	Description
CXM113	PC Board Level, 3-axis Fluxgate Magnetometer

SUNSTAR 商斯达实业集团是集研发、生产、工程、销售、代理经销、技术咨询、信息服务等为一体的高科技企业，是专业高科技电子产品生产厂家，是具有 10 多年历史的专业电子元器件供应商，是中国最早和最大的仓储式连锁规模经营大型综合电子零部件代理分销商之一，是一家专业代理和分销世界各大品牌 IC 芯片和电子元器件的连锁经营综合性国际公司，专业经营进口、国产名厂名牌电子元件，型号、种类齐全。在香港、北京、深圳、上海、西安、成都等全国主要电子市场设有直属分公司和产品展示展销窗口门市部专卖店及代理分销商，已在全国范围内建成强大统一的供货和代理分销网络。我们专业代理经销、开发生产电子元器件、集成电路、传感器、微波光电元器件、工控机/DOC/DOM 电子盘、专用电路、单片机开发、MCU/DSP/ARM/FPGA 软件硬件、二极管、三极管、模块等，是您可靠的一站式现货配套供应商、方案提供商、部件功能模块开发配套商。商斯达实业公司拥有庞大的资料库，有数位毕业于著名高校——有中国电子工业摇篮之称的西安电子科技大学（西军电）并长期从事国防尖端科技研究的高级工程师为您精挑细选、量身订做各种高科技电子元器件，并解决各种技术问题。

更多产品请看本公司产品专用销售网站：

商斯达中国传感器科技信息网：<http://www.sensor-ic.com/>

商斯达工控安防网：<http://www.pc-ps.net/>

商斯达电子元器件网：<http://www.sunstare.com/>

商斯达微波光电产品网：[HTTP://www.rfoe.net/](http://www.rfoe.net/)

商斯达消费电子产品网：<http://www.icasic.com/>

商斯达实业科技产品网：<http://www.sunstars.cn/>

传感器销售热线：

地址：深圳市福田区福华路福庆街鸿图大厦 1602 室

电话：0755-83370250 83376489 83376549 83607652 83370251 82500323

传真：0755-83376182 (0) 13902971329 MSN: SUNS8888@hotmail.com

邮编：518033 E-mail:szss20@163.com QQ: 195847376

深圳赛格展销部：深圳华强北路赛格电子市场 2583 号 电话：0755-83665529 25059422

技术支持：0755-83394033 13501568376

欢迎索取免费详细资料、设计指南和光盘；产品凡多，未能尽录，欢迎来电查询。

北京分公司：北京海淀区知春路 132 号中发电子大厦 3097 号

TEL: 010-81159046 82615020 13501189838 FAX: 010-62543996

上海分公司：上海市北京东路 668 号上海赛格电子市场 2B35 号

TEL: 021-28311762 56703037 13701955389 FAX: 021-56703037

西安分公司：西安高新开发区 20 所(中国电子科技集团导航技术研究所)

西安劳动南路 88 号电子商城二楼 D23 号

TEL: 029-81022619 13072977981 FAX:029-88789382